



Digital Migration Radio MD615

- > Analogue and Digital Dual Mode > Clear Audio
- > Emergency Call Button
- ➤ GPS and Bluetooth Option



www.hytera.co.uk



PROFESSIONAL DEVICE, SIMPLE TO USE

A/D A&D AUTO DETECT

Compatible with analogue conventional and digital conventional modes. This allows the MD615 to simultaneously monitor analogue and digital modes, automatically responding in each mode. This presents an easy solution when migrating from analogue to digital.

POWERFUL COVERAGE

With a high RF power output up to 50W, the MD615 can dramatically increase your communication range.



GPS POSITIONING (Optional)

With an external GPS module and GPS antenna, the MD615 can upload its real-time position to AVL applications.



alloala*

REMOTE CONTROL HEAD (Coming soon)

The remote control head kit increases your installation options, offering flexible positioning for various vehicle types.

ANALOGUE SIGNALING

Supports DTMF and HDC1200 (coming soon) signaling in analogue mode.



RELIABLE AND DURABLE

The MD615 is compliant with MIL-STD-810 C/D/E/F/G and IP54.

PSEUDO TRUNK

Several talk groups share the same frequency, and each one of them can dynamically choose to use one of the slots to talk. This is a two-slot-trunked mode. While time-slot1 is busy, the MD615 will use time-slot 2 to transmit.

RRS RADIO REGISTRATION SERVICE

RRS allows the MD615 to work with SmartDispatch and SmartOne to show online/offline status.

SUPPLEMENTARY FEATURES (Optional)

The MD615 supports radio enable/disable, remote monitor and priority interrupt.



EMERGENCY ALARM/CALL

Use the orange emergency button to initiate an emergency alarm and call to other radios.



BUILT-IN BLUETOOTH (Factory Optional)

With built-in Bluetooth the MD615 can support wireless audio accessories and external PTT devices.



PRIVACY

Basic end-to-end encryption secures your voice and data transmission.



Allows the MD615 to operate in a large multi-site network.

TARGET INDUSTRIES



ACCESSORIES



SPECIFICATIONS

		GENERAL		
Frequency Range		UHF: 400-470MHz; VHF: 136-174MHz		
Channel Capacity		48 (16 channels per zone)		
Zone Capacity		3		
Channel spacing		12.5 / 25 KHz		
Operating Voltage		13.6 V ±15%		
	Standby	around 0.3A		
	Receive	< 1 A		
Current Drain	Transmit -	1W	<3A	
Current Drain		25W	<8A	
		5W	<5A	
		45W	<12A	
Weight		1100g		
Dimensions		164 X 43 X 150 mm		
Frequency Stability		±0.5 ppm		
Antenna Impedance		50Ω		
	т	RANSMITTER		
RF Power Output		Low power version: 1-25W (UHF/VHF) High power version: 5-45W(UHF) / 5-50W(VHF)		
FM Modulation		11K0F3E @ 12.5KHz; 16K0F3E @ 25KHz"		
4FSK Digital Modulation		12.5KHz Data Only: 7K60FXD 12.5KHz Data & Voice: 7K60FXW		
Conducted/Rac	liated Emission	-36dBm<1GHz; -30dBm>1GHz		
Modulation Limiting		±2.5KHz @ 12.5KHz ±5.0KHz @ 25KHz"		
FM Hum & Nois	e	40dB @ 12.5KHz 45dB @ 25KHz"		
Adjacent Chanr	nel Power	60dB @ 12.5KHz; 70dB @ 25KHz		
Audio Response	e	+1 ~ -3dB		
Audio Distortio	n	≤3%		
Digital Vocoder Type		AMBE++ or SELP		
Digital Vocoder	Туре	AMBE++ or SELP		

		RECEIVER	
Sensitivity	Analogue	0.3µV (12dB SINAD); 0.22µV (Typical) (12dB SINAD); 0.4µV (20dB SINAD)	
	Digital	0.3µV /BER5%	
Selectivity	TIA-603	60dB @ 12.5KHz / 70dB @ 25KHz"	
	ETSI	60dB @ 12.5KHz / 70dB @ 25KHz"	
later and define	TIA-603	70dB @ 12.5/25KHz"	
Intermodulation	ETSI	65dB @ 12.5/25KHz"	
Spurious Response	TIA-603	70dB @ 12.5/25KHz"	
Rejection	ETSI	70dB @ 12.5/25KHz	
Placking	TIA-603	90dB	
Blocking	ETSI	84dB	
Hum and Noise		40dB @ 12.5KHz 45dB @ 25KHz [*]	
Rated Audio Power Output		Internal (@16 ohm load)	4W
Nated Addio 1 of	ver output	External (@8 ohm load)	8W
Max Audio Powe	er Output	Internal (@16 ohm load)	6W
		External (@8 ohm load)	12W
Rated Audio Distortion		≤3%	
Audio Response		+1 ~ -3dB	
Conducted Spur		<-57dBm	
		IRONMENTAL	
Operating Temperature		-30°C~ +60°C	
Storage Temper	rature	-40°C~ +85°C	
ESD		IEC 61000-4-2 (Level 4) ±8kV (Contact) ±15kV (Air)	
American Milita	ry Standard	MIL-STD-810 G	
Dustproof & Wa	terproof	IP54 Standard	
Humidity		MIL-STD-810 G Standard	
Shock & Vibratio	on	MIL-STD-810 G Standard	

¹20KHz/25KHz will not be available on new equipment in the U.S. after 2011-01-01. All specifications are subject to change without notice due to continuous development.

Your Hytera partner:



Hytera

Hytera Communications Corporation Limited

Respond & Achieve Address: Hytera Communications (UK) Co. Ltd. Hytera House, 939 Yeovil Road, Slough, Berkshire. SL1 4NH, UK. Tel: +44 (0) 1753 826 120 Fax: +44 (0) 1753 826 121 www.hytera.co.uk info@hytera.co.uk

Further information can be found at: www.hytera.co.uk

Keep up to date with Hytera on social media.





FC CE OO Hytera reserves the right to modify the product design and the specifications. In case of a printing error, Hytera does not accept any liability. All specifications are subject to change without notice.

are subject to change without notice. Encryption features are optional and have to be configured separately.

They are also subject to European export regulations.

H ¥T Hytera are registered trademarks of Hytera Communications Corp. Ltd. © 2017 Hytera Communication Corp., Ltd. All rights reserved.