



# RD625

DMR repeater

The RD625 is a digital repeater designed specifically to provide reliable radio coverage across challenging sites. The RD625 has been developed in accordance with the Digital Mobile Radio (DMR) open ETSI standard and can be operated with either digital or analogue signals.



# Repeater

## RD625

DMR repeater



### Highlights

#### Flexible IP networking

Hytera's DMR repeater can be connected to an IP-based communication network with multiple sites. The roaming function is used to provide radios in this radio network with voice and data services across cells.

#### Connecting VoIP private automatic branch exchanges

The RD625 repeater makes it possible to connect existing VoIP telephone systems to the DMR radio network. This allows DMR radio subscribers to hold half-duplex conversations with participants from the telephone network. Telephone subscribers have the option of making either individual or group calls in the radio network.

#### Analogue and digital operation with the ability to switch automatically

The RD625 repeater can be operated both in analogue and in digital mode and is completely compatible with analogue systems currently in use. The device automatically changes between digital and analogue mode depending on the type of receiver signal, saving both time and money by eliminating the need to configure frequencies and channels manually.

#### Adaptable transmitting power

The integrated power supply of the RD625 can automatically switch to a back-up DC supply from a sealed lead-acid battery if the AC supply fails. This makes it possible to provide a fail-safe solution for critical communications.



### Easy installation

The RD625's well-engineered design makes wall mounting easy using the optionally available wall bracket. This makes it possible to install the repeater flexibly and conveniently in buildings.

### Compact all-in-one design

The RD625's combines transmitter and receiver components, the power supply and the duplexer (optional) in its compact chassis



### Repeater diagnostics and control system (RDAC)

A PC-based application can be used to monitor, inspect and control the RD625. The software supports network access from multiple points and allows administrators to monitor the DMR radio network.

### Repeater access management

To ensure a high level of security, the RD625 features a repeater access monitor that protect the radio network from unauthorized access attempts.

### In the box



EU AC power cable  
PWC03



BRK23 (Duplexer  
mounting bracket)

### Optional accessories



Wall bracket BRK21



DC power cable  
PWC06



Programming cable  
(USB) PC75



Back-to-Back data  
cable PC49

The illustrations above are for reference purposes only. The products might differ from these illustrations. AC Power cable is either UK or Euro. Part number in price books is the same for both UK and Euro versions

## Technical Data

General	
Frequency range	VHF: 136 - 174 MHz UHF: 400 - 470 MHz
Supported operating modes	DMR Tier II (conventional DMR) in accordance with ETSI TS 102 361-1/2/3, analogue
Channel capacity	16
Channel spacing	12.5 / 20 / 25 kHz
Operating voltage	13.6 ± 15% V <sub>cc</sub> 90 V - 264 V <sub>cc</sub>
Max. power consumption (in stand by)	≤ 0.5 A at 13.6 V <sub>cc</sub>
Max. power consumption (during transmission)	≤ 5.5 A at 13.6 V <sub>cc</sub>
Frequency stability	± 0.5 ppm
Antenna impedance	50 Ω
Dimensions (H × W × D)	108 × 210 × 348 mm
Weight	5000 g (with duplexer)

Receiver	
Sensitivity (analogue)	0.3 μV (12 dB SINAD) 0.22 μV (typical) (12 dB SINAD) 0.4 μV (20 dB SINAD)
Sensitivity (digital)	0.3 μV / BER 5 %
<b>Adjacent channel selectivity</b> TIA-603 ETSI	65 dB at 12.5 kHz / 75 dB at 20 / 25 kHz 60 dB at 12.5 kHz / 70 dB at 20 / 25 kHz
<b>Intermodulation</b> TIA-603 ETSI	75 dB at 12.5 kHz / 20 / 25 kHz 70 dB at 12.5 kHz / 20 / 25 kHz
<b>Spurious response rejection</b> TIA-603 ETSI	75 dB at 12.5 kHz / 20 / 25 kHz 70 dB at 12.5 kHz / 20 / 25 kHz
Signal-noise ratio (S/N)	40 dB at 12.5 kHz 43 dB at 20 kHz 45 dB at 25 kHz
Audio distortion	≤ 3 %
Audio sensitivity	+ 1 to - 3 dB
Conducted spurious emission	< - 57 dBm

Your Hytera partner:



### Hytera Communications Corporation Limited

Address: Hytera Communications (UK) Co. Ltd.

Hytera House, 939 Yeovil Road, Slough, Berkshire. SL1 4NH, UK.

Tel: +44 (0) 1753 826 120 Fax: +44 (0) 1753 826 121

www.hytera.co.uk info@hytera.co.uk

Transmitter	
Transmitting power	1 - 25 W (adjustable)
Modulation	11 KDF3E at 12.5 kHz 14 KDF3E at 20 kHz 16 KDF3E at 25 kHz
4FSK digital modulation	12.5 kHz (data only): 7K60FXD 12.5 kHz (data and voice): 7K60FXW
Interfering signals and harmonics	-36dBm (< 1GHz) -30dBm (> 1GHz)
Modulation limiting	± 2.5 kHz at 12.5 kHz ± 4.0 kHz at 20 kHz ± 5.0 kHz at 25 kHz
Hum and noise	40 dB at 12.5 kHz 43 dB at 20 kHz 45 dB at 25 kHz
Adjacent channel selectivity	60 dB at 12.5 kHz 70dB at 20/25kHz
Audio sensitivity	+ 1 to - 3dB
Nominal audio distortion	≤3%
Digital vocoder type	AMBE+2™

Environmental conditions	
Operating temperature range	- 30 °C to + 60 °C
Storage temperature range	- 40 °C to + 85 °C

All technical specifications were tested according to the relevant standards. Subject to change on the basis of continuous development.

Further information can be found at:

[www.hytera.co.uk](http://www.hytera.co.uk)

Keep up to date with Hytera on social media.



Hytera reserves the right to modify the product design and the specifications. In case of a printing error, Hytera does not accept any liability. All specifications are subject to change without notice.

Encryption features are optional and have to be configured separately. They are also subject to European export regulations.

**HYT** Hytera™ are registered trademarks of Hytera Communications Corp. Ltd. © 2017 Hytera Communication Corp., Ltd. All rights reserved.